AMILO Si 1520
Slim sensation –
simply spectacular

The whole greatness in performance and connectivity is packed in this tiny AMILO Si 1520, which is the tiniest one of the AMILO series. With its 12-inch LCD display this notebook assures the mobility which gives you the desired independence of the modern citizen. It is optimized in its size and weight.

With its elegant, slim and stylish design and the BrilliantView display it is a great notebook for all multimedia applications which guarantees you sharp and detailed pictures as well as to be en vogue. Thanks to Intel's Centrino® technology and its power saving modules this notebook delivers extended battery lifetime giving you the independence to work on the move and making this work extremely comfortable. The integrated Wireless LAN enables you to go online wherever you want. A built-in S-Video out port, IEEE 1394, SPDIF and 4 USB 2.0 interfaces are standard to connecting all your digital peripherals and multimedia devices. Additionally the "silent mode" function reduces the fan noise by diminishing the power.

All together the AMILO Si 1520 provides the opportunity to combine professional life with the sunny sides of life.

Features

n Intel® Centrino® Duo mobile technology
   with Intel® Core™ Duo processor up to T2600 or
   with Intel® Core™ 2 Duo processor up to T7200
   or
   Intel® Centrino® mobile technology
   with Intel® Core™ Solo processor up to T1300

n Intel® PRO/Wireless 3945 ABG
   (802.11 a/b/g-Standard)

n 12.0" LCD WXGA (1280 x 800) display with
   BrilliantView Technology

n Ambient Light Sensor for automatically adjustment of
   display brightness depending on ambient light

n Intel® Graphics Media Accelerator 950
   with 128MB shared Memory

n Connect your notebook to external peripherals, storage
   devices or video equipment through the various USB
   2.0, SPDIF, DVI-I and IEEE 1394 ports and Bluetooth®
   connection

n Up to 2GB DDR2 in 2 SO-DIMM slot

n Silent Mode functionality

n Windows Vista™ or Windows® XP
   and Application Software

Operating system
Microsoft® Windows® XP Home
Windows Vista™ Capable[1]
or
Windows Vista™ Home Basic[2]
or
Windows Vista™ Home Premium[2]

Fujitsu Siemens Computers recommends
Windows Vista™ Home Premium

Optional Application Software
Microsoft® Works Suite[3]
Microsoft® Entertainment Pack[3]
Microsoft® Works + Office Trial STE Edition[3]
Adobe Photoshop Elements 3.0[3]
Magix Media Suite[3]
WinDVD[3] or Vista DVD Playback Pack
Nero burning ROM[3] or Nero 7 Essential
Adobe Reader
Norton Internet Security Suite or Norman Anti-Virus
Country specific Internet Service Providers

Manual, Safety Guide and Warranty Guide

Drivers and Utility
Drivers and Utility DVD included.
Updates downloadable at
http://www.fujitsu-siemens.com

System, processor, architecture
Chipset: Intel® 945GM+ICH7-M
CPU:　　Intel® Core™ **Duo** processor
　　　　　T2300E (1.66GHz, 667 MHz, 2MB L2 cache)
　　　　　T2400 (1.83GHz, 667 MHz, 2MB L2 cache)
　　　　　T2500 (2.0GHz, 667 MHz, 2MB L2 cache)
　　　　　T2600 (2.16GHz, 667 MHz, 2MB L2 cache)

　　　　　Intel® Core™ **2 Duo** processor
　　　　　T5500 (1.66GHz, 667 MHz, 2MB L2 cache)
　　　　　T5600 (1.83GHz, 667 MHz, 2MB L2 cache)
　　　　　T7200 (2.0GHz, 667 MHz, 4MB L2 cache)

　　　　　Intel® Core™ **Solo** processor
　　　　　T1300 (1.66GHz, 667 MHz, 2MB L2 cache)

Memory
2 SO-DIMM memory slots (no memory on board)
256MB DDR2 533MHz
512MB DDR2 533MHz
1GB DDR2 533MHz

Storage devices/drives
HDD:
SATA HDD (5400rpm):
60, 80, 100 and 120GB SATA hard disk
ODD:
8x Multi-format DVD burner with double layer
Read speed: CD-ROM 24x, DVD-ROM 8x
Write speed: CD-R 24x, CD-RW16x, DVD+R8x,
　　　　　　　DVD-R 8x, DVD+RW 6x, DVD-RW 6x,
　　　　　　　DVD+R DL (Double Layer 8.5GB) 2,4x,
　　　　　　　DVD-R DL (Double Layer 8.5GB) 4x

Display
12.0" LCD WXGA BrilliantView
Resolution (physic.):　　　　　　　　1280x800
ISO 13406-2 class II

ACPI functions
S1 LCD off
S3 save to RAM
S4 save to disk
S5 soft off
Silent Mode

Graphics
Intel® Graphic Media Accelerator 950 integrated
in Intel 945GM chipset, up to 128MB (shared)
- Supports DX9
- Dynamic Video memory technology (DVMT) 3.0 support
- Intel smart 2D display technology

I/O Interfaces
1x IEEE1394, 4x USB 2.0 ports, 1x S-Video out
1x DVI-I, 1x modem, 1x LAN, 1x WLAN, 1x BT
1x ExpressCard slot (34/54mm)
1x headphone out combined with 1x SPDIF
1x microphone in combined with 1x line in,
1x power supply
1x 4-in-1 card reader SD/MS/MMC/MS pro

Communications
- Built-in 56K, V.92 fax modem
- 10/100Mbps LAN
- Integrated Bluetooth® 2.0
- Integrated Wireless LAN (WLAN) solution 802.11a/b/g:
  Intel® PRO/Wireless 3945ABG
　　- speeds up to 54Mbps
　　- industry standard Wireless LAN security support
　　- Intel® Intelligent Scanning Technology for optimal
　　　power management
For use in BE, CH, DK, DE, EE, FI, FR, EL, IE, IS, IT, LI,
LV, LT, LU, MT, NL, NO, PL, AT, PT, SE, SK, ES, CZ, HU,
UK, CY, NL

Audio
Support of HD audio for SP/DIF output with up to 7.1
channels, 2 built-in speakers, built-in array microphone,
Connectors: microphone in combined with line-in,
headphone out shared with. SPDIF support
volume regulator per function key

Launch Keys
6 Launch Keys located on top of the keyboard enabling the
user to launch the following applications:
- E-mail
- Internet browser
- Silent mode (reduce noise level / fan speed, by reducing
  the CPU & VGA performance)
  (Office applications, Internet and DVD playback are not
  affected)
- WLAN/BT on/off
- Power on/off
- Multimedia application button

Hot Keys

The following hotkeys or key combinations are available:

Fn-Esc   Enable/Disable Bluetooth®
Fn-F1   Suspend
Fn-F2   Enable/Disable WLAN
Fn-F3   Display toggle, switches display output between display screen and external monitor
Fn-F4   Increase display brightness
Fn-F5   Decrease display brightness
Fn-F6   Mute
Fn-F7   Decrease speaker volume
Fn-F8   Increase speaker volume
Fn-F9   Start Player/ Pause
Fn-F10   Stop Player
Fn-F11   Previous Track
Fn-F12   Next Track
Fn-Backspace   Light Sensor Enable/Disable

Pointing device & control buttons

Touchpad with a left and right mouse button
Power button / lid switch

Status indicator

The notebook has 6 status icons:
Caps lock
Num lock
Media activity (ODD/HDD)
Power status (& suspend)
RF (BT & WLAN) on / off
Battery status charging / full / low

Security

Supervisor password
Kensington Lock

Power system

Li-Ion battery, 6 cells, 10.8V / 11.1V / 4800mAh
Approximately 4 hrs battery runtime, depending on usage[4]
Dynamic charge supported
ACPI 2.0 supported
External universal AC adapter: 100 - 240 V AC, 50 - 60Hz,
Output: 65 W with 20 V DC, 3.25 A

Dimensions and weight

Dimensions (H x W x D):   ~23.9 / ~32 x 299 x 220mm
Weight: 1.7kg[5]

Operating conditions

Operational: 5°C to 35°C (ambient temperature)
10% to 90% relative humidity, non-condensing

Certifications

CE Marking
R&TTE (WLAN)

Warranty

Country specific terms

Accessories (optional)

AC adapter 65W: FSP: 805N00047
                        SAP: 10600737246
                        EAN: 4045827693642

First Battery 6-cell: FSP: 805N00041
                        SAP: 10600737199
                        EAN: 4045827693178
Car adapter   S26391-F2613-L600)

1) Not all Windows Vista™ features are available for use on all Windows Vista Capable PCs. All Windows Vista Capable PCs will run the core experiences of Windows Vista, such as innovations in organizing and finding information, security, and reliability. Some features available in premium editions of Windows Vista - like the new Windows® Aero™ user interface - require advanced or additional hardware. Check www.windowsvista.com/getready for details.
2) Windows Vista™ Home Basic and Windows Vista™ Home Premium are available from January 30th, 2007 (depending on language).
3) Is only included for Windows® XP Home Edition or Windows® XP Media Center Edition.
4) Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Recharge time varies depending on usage. The recharge capacity may decrease after some moths so that the battery lifetime as well as operating time can not be assured for the whole lifetime of the notebook.
5) Weight may vary depending on actual configuration